



ENERGY STAR CERTIFIED

# Electric Vehicle Chargers (AC-Output)

## Andeman - EV Portable Charger : HS1

### Specifications

<b>Brand Name:</b>	Andeman
<b>Model Name:</b>	EV Portable Charger
<b>Model Number:</b>	HS1
<b>ENERGY STAR Unique ID:</b>	3387702
<b>ENERGY STAR Partner:</b>	SUI CHENG LIMITED
<b>Product Type:</b>	Level 2
<b>Input Voltage (V):</b>	240.0
<b>Max Nameplate Output Current (A):</b>	32
<b>Maximum Output Power (kW):</b>	7.68
<b>Number of Outputs:</b>	1
<b>Maximum Output Cord Length (ft.):</b>	25
<b>Output Cord Gauge (AWG):</b>	10
<b>Maximum (100%) Measured Luminance of the High Res Display (candelas per m2):</b>	100.0
<b>Automatic Brightness Control (ABC) Capable?:</b>	No
<b>Connected Capable:</b>	Yes
<b>Connects Using:</b>	Wi-Fi
<b>Network Connection Types Available:</b>	Wi-Fi or Gigabit Ethernet
<b>DR Protocol:</b>	Open Charge Point Protocol (OCPP)
<b>Protocols Used to Support Smart Charging:</b>	SAE J1772
<b>Screen Area, if EVSE has high res display (in2):</b>	1.5
<b>15 A Operation Mode Test: Total Loss (watts):</b>	28.5
<b>30 A Operation Mode Test: Total Loss (watts):</b>	67.2
<b>4 A Operation Mode Test: Total Loss (watts):</b>	14.1
<b>Full Current Operation Mode Test: Total Loss (watts):</b>	88.5
<b>Idle Mode Input Power (watts):</b>	4.93
<b>Idle Mode Power Factor:</b>	0.32
<b>Idle Mode Total Allowance (watts):</b>	17.96
<b>No Vehicle Mode Input Power (watts):</b>	2.52
<b>No Vehicle Mode Power Factor:</b>	0.24
<b>No Vehicle Mode Total Allowance (watts):</b>	5.16
<b>Partial On Mode Input Power (watts):</b>	2.5
<b>Partial On Mode Power Factor:</b>	0.26

<b>Partial On Mode Total Allowance (watts):</b>	5.16
<b>Date Certified:</b>	2024-01-24
<b>Date Available on Market:</b>	2024-01-24
<b>Markets:</b>	United States, Canada
<b>ENERGY STAR Certified:</b>	Yes

**Captured On:**  
04/25/2025