

## CyberPower - OR2200PFCRT2U : OR2200PFCRT2U

| Specifications  |                          |
|---|--------------------------|
| ENERGY STAR Unique ID:  | 2331986                  |
| Brand Name:   | CyberPower               |
| Model Name:   | OR2200PFCRT2U            |
| Model Number:   | OR2200PFCRT2U            |
| Power Conversion Mechanism:   | Static                   |
| Minimum Configuration Tested Model<br>Number:                           | OR2200PFCRT2U            |
| Active Output Power Rating Minimum<br>Configuration (W):                | 1540                     |
| Apparent Output Power Rating Minimum<br>Configuration (VA):             | 2000                     |
| Topology (ac):  | Line Interactive         |
| Topology and Product Type Combined:                                     | ac Line Interactive (VI) |
| Application:  | Commercial,Consumer      |
| Rated Input Voltage (V rms):  | 120-120                  |
| Rated Input Frequency (Hz):   | 60-60                    |
| Rated Output Voltage (V):   | 120-120                  |
| Rated Output Frequency (Hz):  | 60-60                    |
| Rack Mountable:   | Yes                      |
| Rack Mount Height (U):  | 2                        |
| Height (mm):  | 433                      |
| Width (mm):   | 88                       |
| Depth (mm):   | 400                      |
| Normal Mode(s) Input Dependency<br>Characteristic (ac):                 | Voltage Independent      |
| Modular UPS:  | No                       |
| Number of Normal Modes:   | Single-normal-mode       |
| Default Normal Mode (ac):   | Voltage Independent      |
| Test Input Voltage (V rms):   | 120                      |
| Test Input Frequency (Hz):  | 60                       |
| Test Output Voltage (V):  | 120                      |
| Test Output Frequency (Hz):   | 60                       |
| Total Input Power in W at 0% Load Min Config<br>Lowest Dependency (ac): | 3.1                      |
|   |                          |

| Efficiency at 25% Load Min Config Lowest<br>Dependency (ac):  | 98.6   |
|---|--|
| Efficiency at 50% Load Min Config Lowest<br>Dependency (ac):  | 98.6   |
| Efficiency at 75% Load Min Config Lowest<br>Dependency (ac):  | 98.3   |
| Efficiency at 100% Load Min Config Lowest<br>Dependency (ac): | 97.7   |
| Weighted Efficiency Calc Min Config Lowest<br>Dependency:     | 98.2   |
| Efficiency (%):   | 98.2   |
| Modular UPS Module Tested Model Number:                       | N/A  |
| Energy Storage Mechanism:                                     | Battery  |
| Energy Storage System Technology:                             | Valve Regulated Lead-acid Battery                            |
| Energy Storage System Configuration:                          | Integral   |
| Energy Storage System Removable to Another Room:              | No   |
| Energy Storage System Runtime at 100% Load (min.):            | 3  |
| Energy Storage System Runtime at 50% Load (min.):             | 13   |
| Energy Storage System Warranty (yrs):                         | 1  |
| Energy Storage System Information URL:                        | N/A  |
| Network Connections Available:                                | Serial Port,USB Port   |
| Communication Protocols:                                      | Other  |
| Communication Protocol Other:                                 | HID, CyberPower serial Protocol (v2)                         |
| Manufacturer Take Back Program:                               | Yes  |
| Model Web Page URL:   | https://www.cyberpowersystems.com/product/ups/or2200pfcrt2u/ |
| Test Method Guidelines:                                       | N/A  |
| Date Available on Market:                                     | 2019-01-01   |
| Date Certified:   | 2018-12-24   |
| Markets:  | United States, Canada  |
| ENERGY STAR Certified:  | Yes  |
|   |  |

## Additional Model Information

OR2200PFCRT2UTAA,OR2200PFCRT2UTAA,

Captured On: 04/28/2025